ignion[™]

Your innovation. Accelerated.

Unleash your antenna efficiency with best clearance and PCB size

APPLICATION NOTE ALL mXTEND[™] (NN02-220)

TABLE OF CONTENTS

1. PF	RODUCT DESCRIPTION NN02-220	3
2. CI	LEARANCE LENGTH EXPERIMENTS	4
2.1.	EVALUATION BOARD	4
2.2.	VSWR AND EFFICIENCY	5
2.3.	MATCHING NETWORK	5
3. GI	ROUND PLANE LENGTH EXPERIMENTS	7
3.1.	EVALUATION BOARD	7
3.2.	VSWR AND EFFICIENCY	8
3.3.	MATCHING NETWORK	8

1. PRODUCT DESCRIPTION NN02-220

The ALL mXTEND[™] chip antenna component (NN02-220) has been specifically designed for providing multiband performance in wireless devices (particularly in mobile devices), enabling worldwide coverage by allowing operation in the communication standards GSM850, GSM900, GSM1800/DCS, GSM1900/PCS, UMTS, LTE700, LTE800, LTE850, LTE900, LTE1700, LTE1800, LTE1900, LTE2000, LTE2100, LTE2300, LTE2500, and LTE2600.



Material: The ALL mXTEND[™] chip antenna component is built on glass epoxy substrate.

APPLICATIONS

- Handsets
- Smartphones
- Tablets
- Laptop PCs
- Netbooks
- Modules
- Routers
- Smart meters
- Tracking devices

BENEFITS

- High efficiency
- Small size
- Cost-effective
- Easy-to-use (pick and place)
- Multiband behaviour (worldwide standards)
- Off-the-Shelf Standard Product (no customization is required)

The ALL mXTEND[™] chip antenna component belongs to a new generation of antenna solutions based on the Virtual Antenna[™] technology owned by Ignion. The technology is mainly focused on replacing conventional antenna solutions by miniature and standard components.

This project has received funding from the European Union's Horizon 2020 research and innovation programme under grant agreement N° 674491



2. CLEARANCE LENGTH EXPERIMENTS

2.1 EVALUATION BOARD

This Evaluation Board EB_NN02-220-1B-2R-1P integrates an UFL cable to connect the ALL mXTEND[™] chip antenna component with a SMA connector. The experiment consists of reducing the clearance length, going from 45mm (original case) to 25mm.



Clearance Length: 45 mm x 12mm



Clearance Length: 27 mm x 12mm

Measure	mm
Α	142
В	60
С	45 – 25
D	12

Tolerance: ±0.2 mm



Clearance Length: 30 mm x 12mm



Clearance Length: 25 mm x 12mm

D: Distance between the edge of the PCB and the ground plane.

Clearance Area: C x D. D is fixed meanwhile C varies.

Material: The evaluation board is built on FR4 substrate. Thickness is 1 mm.

Figure 1 – Evaluation boards with different clearance lengths operating at ranges 698 – 960MHz and 1710 – 2690MHz.

2.2 VSWR AND EFFICIENCY

VSWR (Voltage Standing Wave Ratio) and Total Efficiency versus Frequency (GHz).



Figure 2 – VSWR and Total Efficiency for the 698 – 960 MHz frequency range and for the 1710 – 2690 MHz frequency range from the evaluation board (Figure 1).

		LFR (69	8 – 960	MHz)		HFR (1710 – 2690MHz)				
С	ቢ а 698MHz	ቢ а 960MHz	Min	Max	Av. η _a	ղ a 1710MHz	ቢ а 2690MHz	Min	Max	Αv. ηa
45mm	32.8	55.0	32.8	71.5	56.6	71.4	68.9	68.0	86.0	76.5
30mm	35.4	46.8	35.4	62.2	50.6	68.2	65.0	61.1	77.5	70.6
27mm	29.4	48.0	29.4	62.3	49.1	55.7	62.0	55.7	74.7	68.6
25mm	34.5	30.0	30.0	49.7	41.8	56.1	42.0	40.9	62.7	52.5

Table 1 – Antenna efficiency (%) comparison considering the different clearance lengths.

2.3 MATCHING NETWORK

The specs of a Ignion standard product are measured in their evaluation board, which is an ideal case. In a real design, components nearby the antenna, LCD's, batteries, covers, connectors, etc. affect the antenna performance. This is the reason why it is highly recommended placing pads compatible with 0402 and 0603 SMD components for a matching network as close as possible to the feeding point. Do it in the ground plane area, not in the clearance area. This provides a degree of freedom to tune the ALL mXTEND[™] chip antenna component once the design is finished and taking into account all elements of the system (batteries, displays, covers, etc.).

Please notice that different devices with different ground planes and different components nearby the ALL mXTEND[™] chip antenna component may need a different matching network. To ensure optimal results, the use of high Q and tight tolerance components is highly recommended (Murata components). If you need assistance to design your matching network, please contact <u>support@ignion.io</u>, or try our free-of-charge¹ <u>Antenna Intelligence Cloud</u> design service, which will get you a chip antenna design including a custom matching network for your



device in 24h¹. Other information related to Ingion's range of R&D services is available at: <u>https://www.ignion.io/rdservices/</u>



Figure 3 – Topology of matching network mounted for the different solutions.

С	Z 1	Z ₂	Z ₃	Z 4	Z 5	Z ₆	Z ₇
45mm	4.7 nH	12 nH	1.2 pF	1.1 pF	9.1 nH	2.0 pF	2.2 nH
30mm	4.7 nH	12 nH	1.2 pF	1.1 pF	9.1 nH	1.8 pF	2.4 nH
27mm	4.7 nH	12 nH	1.2 pF	1.1 pF	9.1 nH	1.8 pF	2.2 nH
25mm	4.7 nH	12 nH	1.2 pF	1.1 pF	9.1 nH	2.0 pF	2.2 nH

Table 2 – Values of the components for each clearance length.

Component	Value	Part Number		
Z1	4.7 nH	LQW15AN4N7B80		
Z2	12 nH	LQW15AN12NG00		
Z3	1.2 pF	GJM1555C1H1R2WB01		
Z4	1.1 pF	GJM1555C1H1R1WB01		
Z5	9.1 nH	LQW15AN9N1G00		
76	2.0 pF	GJM1555C1H2R0WB01		
20	1.8 pF	GJM1555C1H1R8WB01		
77	2.2 nH	LQW15AN2N2B80		
21	2.4 nH	LQW15AN2N4B80		

Table 3 – Values and part numbers of the components used for the matching networks for the cases with clearance length equal to 45 mm, 30 mm, 27 mm and 25 mm.

¹ See terms and conditions for a free Antenna Intelligence Cloud service in 24h at: <u>https://www.ignion.io/antenna-intelligence/</u>

3. GROUND PLANE LENGTH EXPERIMENTS

3.1 EVALUATION BOARD

This Evaluation Board EB_NN02-220-1B-2R-1P integrates an UFL cable to connect the ALL mXTEND[™] chip antenna component with a SMA connector. The experiment consists of reducing the ground plane length, going from 130mm (original case) to 40mm.







Ground plane Length: 130 mm

Measure	mm
Α	142-52
В	60
С	45
D	12
E	130-40

Tolerance: ±0.2 mm

Ground plane Length: 100 mm

Ground plane Length: 60mm

D: Distance between the edge of the PCB and the ground plane.

Clearance Area: 45mm x 12mm (C x D).

Material: The evaluation board is built on FR4 substrate. Thickness is 1 mm.

Figure 4 – Evaluation boards with different ground plane lengths operating at ranges 698 – 960MHz and 1710 – 2690MHz.

3.2 VSWR AND EFFICIENCY

VSWR (Voltage Standing Wave Ratio) and Total Efficiency versus Frequency (GHz).



Figure 5 – VSWR and Total Efficiency for the 698 – 960 MHz frequency range and for the 1710 – 2690 MHz frequency range from the evaluation board (Figure 4).

		LFR (69	8 – 960	MHz)		HFR (1710 – 2690MHz)				
E	ቢ а 698MHz	ቢ а 960MHz	Min	Max	Αv. ηa	ቢ а 1710MHz	ቢ а 2690MHz	Min	Max	Αv. ηa
130mm	36.2	54.1	36.2	67.7	53.9	72.5	63.3	62.7	79.3	70.5
120mm	28.8	49.4	28.8	67.1	50.8	75.1	65.8	61.3	84.3	72.5
100mm	17.8	53.0	17.8	65.0	44.7	77.0	63.1	62.7	86.1	75.3
80mm	14.8	30.7	14.8	40.0	28.3	73.4	69.5	64.5	83.4	74.1
60mm	12.8	20.9	12.8	24.2	19.7	72.3	58.2	57.1	75.2	65.7
40mm	3.9	23.5	3.9	23.5	13.3	54.6	82.2	49.6	85.4	76.4

Table 4 – Antenna efficiency (%) comparison considering the different ground plane lengths.

3.3 MATCHING NETWORK

The specs of a Ignion standard product are measured in their evaluation board, which is an ideal case. In a real design, components nearby the antenna, LCD's, batteries, covers, connectors, etc. affect the antenna performance. This is the reason why it is highly recommended placing pads compatible with 0402 and 0603 SMD components for a matching network as close as possible to the feeding point. Do it in the ground plane area, not in the clearance area. This provides a degree of freedom to tune the ALL mXTEND[™] chip antenna component once the design is finished and taking into account all elements of the system (batteries, displays, covers, etc.).

Please notice that different devices with different ground planes and different components nearby the ALL mXTEND[™] chip antenna component may need a different matching network. To ensure optimal results, the use of high Q and tight tolerance components is highly recommended (Murata components). If you need assistance to design your matching network, please contact <u>support@ignion.io</u>, or try our free-of-charge¹ <u>Antenna Intelligence Cloud</u> design service, which will get you a chip antenna design including a custom matching network for your device in 24h². Other information related to Ingion's range of R&D services is available at: <u>https://www.ignion.io/rdservices/</u>

² See terms and conditions for a free Antenna Intelligence Cloud service in 24h at: <u>https://www.ignion.io/antenna-intelligence/</u>





Figure 6 – Topology of matching network mounted for the different solutions.

E	Z 1	Z ₂	Z ₃	Z 4	Z ₅	Z ₆	Z ₇
130mm	4.7 nH	12 nH	1.2 pF	1.1 pF	9.1 nH	2.0 pF	2.2 nH
120mm	4.7 nH	12 nH	1.2 pF	1.1 pF	9.1 nH	2.2 pF	2.2 nH
100mm	4.7 nH	12 nH	1.2 pF	1.1 pF	9.1 nH	2.2 pF	2.2 nH
80mm	4.7 nH	13 nH	1.2 pF	1.1 pF	9.1 nH	2.2 pF	2.2 nH
60mm	4.7 nH	13 nH	1.2 pF	1.1 pF	9.1 nH	2.5 pF	2.2 nH
40mm	0 Ω	12 nH	1.2 pF	0.5 pF	9.1 nH	2.2 pF	2.2 nH

Table 5 – Values of the components for each clearance length.

Component	Value	Part Number		
Z1	4.7 nH	LQW15AN4N7B80		
70	12 nH	LQW15AN12NG00		
	13 nH	LQW15AN13NG00		
Z3	1.2 pF	GJM1555C1H1R2WB01		
74	0.5 pF	GJM1555C1HR50WB01		
Ζ4	1.1 pF	GJM1555C1H1R1WB01		
Z5	9.1 nH	LQW15AN9N1G00		
	2.0 pF	GJM1555C1H2R0WB01		
Z6	2.2 pF	GJM1555C1H2R2WB01		
	2.5 pF	GJM1555C1H2R5WB01		
Z7	2.2 nH	LQW15AN2N2B80		

Table 6 – Values and part numbers of the components used for the matching networks for the cases with ground plane length equal to 130 mm, 120 mm, 100 mm, 80 mm, 60 mm, and 40 mm.

ignion[™]

Your innovation. Accelerated.

Contact: support@ignion.io +34 935 660 710

Barcelona

Av. Alcalde Barnils, 64-68 Modul C, 3a pl. Sant Cugat del Vallés 08174 Barcelona Spain

Shanghai

Shanghai Bund Centre 18/F Bund Centre, 222 Yan'an Road East, Huangpu District Shanghai, 200002 China

New Dehli

New Delhi, Red Fort Capital Parsvnath Towers Bhai Veer Singh Marg, Gole Market, New Delhi, 110001 India

Tampa

8875 Hidden River Parkway Suite 300 Tampa, FL 33637 USA